

## Model DQ20

Sleep mode (slow wake up)					
AC Mains Power Draw (Watts)	Current Draw (Amps)		Thermal Dissipation		
	120Vac	230Vac	Watts	kcal/hr	btu/hr
4.5	0.4	0.2	4.5	4	15

Standby mode (fast wake up)					
AC Mains Power Draw (Watts)	Current Draw (Amps)		Thermal Dissipation		
	120Vac	230Vac	Watts	kcal/hr	btu/hr
60	1.0	0.5	60	52	205

Running with no audio signal					
AC Mains Power Draw (Watts)	Current Draw (Amps)		Thermal Dissipation		
	120Vac	230Vac	Watts	kcal/hr	btu/hr
195	2.9	1.5	195	168	665

Running in 2 Ohm mode* (all channels driven)							
Load (Ohms)	Signal duty & Crest Factor	Input power (Watts)	Current Draw (Amps)		Thermal Dissipation		
			120Vac	230Vac	Watts	kcal/hr	btu/hr
2	1/8, cf = 4.0 (12dB)	3000	33.5**	17.5	500	430	1706
4	1/4, cf = 2.8 (9dB)	3475	38.8**	20.3	475	408	1621
4	1/8, cf = 4.0 (12dB)	1780	19.7	10.3	280	241	955
8	1/4, cf = 2.8 (9dB)	1750	19.2	10.0	250	215	853
8	1/8, cf = 4.0 (12dB)	975	11.0	5.8	225	193	767

### Notes

- The amplifier was configured to have no audio processing
- Measurements were performed with a Hameg HM8115-2 power analyser
- All measurements were done at 230Vac, 50Hz.
- The Current Draw figures for 120Vac are calculated
- \*The DQ20 does not have 4 & 8 Ohm Low Z modes
- \*\*The EBP limiter should be set to 32A, but will not activate on any sensible program material

# Model DQ10

Sleep mode (slow wake up)					
AC Mains Power Draw (Watts)	Current Draw (Amps)		Thermal Dissipation		
	120Vac	230Vac	Watts	kcal/hr	btu/hr
4.5	0.4	0.2	4.5	4	15

Standby mode (fast wake up)					
AC Mains Power Draw (Watts)	Current Draw (Amps)		Thermal Dissipation		
	120Vac	230Vac	Watts	kcal/hr	btu/hr
60	1.0	0.5	60	52	205

Running with no audio signal					
AC Mains Power Draw (Watts)	Current Draw (Amps)		Thermal Dissipation		
	120Vac	230Vac	Watts	kcal/hr	btu/hr
195	2.9	1.5	195	168	665

Running (all channels driven)								
Load Mode	Load (Ohms)	Signal duty & Crest Factor	Input power (Watts)	Input Current (Amps)		Thermal Dissipation		
				120Vac	230Vac	Watts	kcal/hr	btu/hr
2 Ohm	2	1/8, cf = 4.0 (12dB)	1600	19.2	10.0	350	301	1194
2 Ohm	4	1/4, cf = 2.8 (9dB)	1560	18.7	9.8	310	267	1058
2 Ohm	4	1/8, cf = 4.0 (12dB)	875	11.1	5.8	250	215	853
4 Ohm	4	1/4, cf = 2.8 (9dB)	2920	31.0	16.2	420	361	1133
4 Ohm	4	1/8, cf = 4.0 (12dB)	1550	19.2	10.0	300	258	1024
4 Ohm	8	1/4, cf = 2.8 (9dB)	1535	18.4	9.6	285	245	973
4 Ohm	8	1/8, cf = 4.0 (12dB)	864	10.9	5.7	239	206	816
8 Ohm	8	1/4, cf = 2.8 (9dB)	1800	21.1	11.0	300	258	1024
8 Ohm	8	1/8, cf = 4.0 (12dB)	975	11.5	6.0	225	193	768

## Notes

- The amplifier was configured to have no audio processing
- Measurements were performed with a Hameg HM8115-2 power analyser
- All measurements were done at 230Vac, 50Hz.
- The Current Draw figures for 120Vac are calculated

# Model DQ6

Sleep mode (slow wake up)					
AC Mains Power Draw (Watts)	Current Draw (Amps)		Thermal Dissipation		
	120Vac	230Vac	Watts	kcal/hr	btu/hr
4.5	0.4	0.2	4.5	4	15

Standby mode (fast wake up)					
AC Mains Power Draw (Watts)	Current Draw (Amps)		Thermal Dissipation		
	120Vac	230Vac	Watts	kcal/hr	btu/hr
60	1.0	0.5	60	52	205

Running with no audio signal					
AC Mains Power Draw (Watts)	Current Draw (Amps)		Thermal Dissipation		
	120Vac	230Vac	Watts	kcal/hr	btu/hr
132	2.9	1.5	132	114	450

Running (all channels driven)								
Load Mode	Load (Ohms)	Signal duty & Crest Factor	Input power (Watts)	Input Current (Amps)		Thermal Dissipation		
				120Vac	230Vac	Watts	kcal/hr	btu/hr
2 Ohm	2	1/8, cf = 4.0 (12dB)	1022	12.8	6.7	272	234	928
2 Ohm	4	1/4, cf = 2.8 (9dB)	991	12.5	6.5	241	207	822
2 Ohm	4	1/8, cf = 4.0 (12dB)	563	7.9	4.1	188	162	642
4 Ohm	4	1/4, cf = 2.8 (9dB)	1780	21.1	11.0	280	241	955
4 Ohm	4	1/8, cf = 4.0 (12dB)	970	11.5	6.0	220	189	751
4 Ohm	8	1/4, cf = 2.8 (9dB)	963	11.5	6.0	213	183	727
4 Ohm	8	1/8, cf = 4.0 (12dB)	552	7.3	3.8	177	152	604
8 Ohm	8	1/4, cf = 2.8 (9dB)	1695	19.2	10.0	195	168	665
8 Ohm	8	1/8, cf = 4.0 (12dB)	940	11.5	6.0	190	163	648

## Notes

- The amplifier was configured to have no audio processing
- Measurements were performed with a Hameg HM8115-2 power analyser
- All measurements were done at 230Vac, 50Hz.
- The Current Draw figures for 120Vac are calculated